

1 **A ferrite-filled cavity resonator for electronic article surveillance on metallic packaging**

2 P.S. Keatley, E.R. Glover, B. Tremain, I.R. Hooper, A.P. Hibbins, and R.J. Hicken

3 *Department of Physics and Astronomy, University of Exeter, Stocker Road, EXETER, EX4 4QL,*
4 *UK*

5

6 **Abstract**

7 Conventional electronic article surveillance (EAS) tags are ineffective on metallic
8 packaging. The component of RF magnetic field perpendicular to the surface of the packaging
9 induces eddy currents that suppress the magnetic flux linking the inductive element of the tag.
10 In this work an inductive quarter-wavelength planar cavity, formed by wrapping aluminum foil
11 around a ferrite core, was extended by wrapping additional capacitive layers of foil/dielectric
12 around the ferrite-filled central region. This so-called ‘wrapped tag’ exhibits the frequency, Q -
13 factor, and read distance characteristics of existing EAS tags, but is instead driven by RF
14 magnetic fields parallel to the surface of the metallic packaging. In this article we compare the
15 observed frequency response of the wrapped tag with a simple LC -resonator model that takes
16 account of the tag’s geometrical features, and use the model to describe how the design and
17 construction of the tag can be optimized. Finite element method modeling is used to reveal
18 how the current flows in the wrapped foil of the tag. Prototype tags show good reproducibility,
19 demonstrating the potential of the design as a solution to the problem of tagging metallic
20 packaging in the EAS industry.

21

22


1 **Introduction**

2 Microwave cavity resonators are a key component of electromagnetic technology that
3 enjoy ubiquitous use[1], from high power microwave sources[2] and exotic particle
4 detectors[3], to filters and absorbers[4] of microwave radiation. The challenge for everyday
5 technology is to construct resonators in compact formats with dimensions that are small
6 compared to the free space wavelength. A planar cavity can be defined from a pair of infinite
7 parallel conducting planes separated by an insulator that can support a transverse
8 electromagnetic (TEM) mode with no low frequency cut off [5]. The planes can be truncated
9 to form a one-dimensional cavity with infinite width, and length that is much greater than the
10 separation of the planes. The cavity can support a standing wave resonance of the TEM mode,
11 with electric field antinodes at the open ends of the cavity, when its length is equal to a half-
12 integer multiple of the mode wavelength [6]. If the planes are electrically connected at one end
13 of the cavity, the electric field exhibits a node at the closed end [7, 8]. Such a cavity can support
14 a quarter-wavelength mode and is analogous to an organ pipe cavity.

15 Previously it was reported that ferrite-filled quarter-wavelength cavities can act as
16 compact planar resonators that have potential for use in electronic article surveillance (EAS)
17 applications [9]. EAS tags are typically used to alert retailers to the unauthorized removal of
18 goods from their premises. It is usually necessary for such tags to be discreet, covering only a
19 small area of the product and having a low profile on its surface. It was shown that for a given
20 frequency, and similar cavity width and thickness, the use of a ferrite filling material allowed
21 the length of a planar cavity resonator to be reduced to approximately one quarter of the length
22 of a similar cavity filled with Teflon. However, the frequency of the ferrite-filled cavity of
23 $\sim 10^2$ MHz still far exceeded that required for EAS at 8.2 MHz. In the present work it is shown
24 how such a cavity can be modified to yield a discreet, low profile tag that operates at 8.2 MHz
25 on conducting materials. This much lower frequency was achieved by extending the length of
26 the cavity with a thin dielectric-filled section that could then be wrapped around the shorter
27 ferrite-filled section. The dielectric-filled section increases the capacitance of the structure. The
28 use of a ferrite with high permeability and low loss enhances the self-inductance and quality
29 factor so that coupling to the magnetic field from an EAS gate system is comparable to that of
30 existing EAS tags.

31 Existing commercial 8.2 MHz EAS tags consist of an air core coil inductor and a
32 capacitor connected in series to form an *LC*-resonator. The cross-sectional area of the inductor
33 must be sufficiently large as to ensure adequate sensitivity for detection at the desired read
34 distance. The capacitance is then chosen to achieve a frequency of 8.2 MHz. Such a tag can

1 be readily constructed using a 5-turn cylindrical wire coil with 65 mm diameter in series with
2 a 120 pF ceramic capacitor, Figure 1(a).



3

4 Figure 1. (a) A hard tag constructed from a wire coil inductor in series with a capacitor. (b) A
5 deactivatable label tag constructed from a planar spiral inductor in series with a thin film capacitor.

6

7 The coil and capacitor of these so-called ‘hard tags’ results in a bulky tag that cannot be
8 deactivated, and which must therefore be removed at the point of sale. More discreet adhesive
9 ‘label tags’, e.g. [10], instead consist of an etched Al planar spiral inductor on a polyester
10 substrate that surrounds a deactivatable thin film capacitor formed from a thinned region of the
11 polyester with an Al electrode on either side, Figure 1(b). These disposable tags can be
12 deactivated at the point of sale, by inducing a short-circuit between the plates of the capacitor
13 and can remain on the product after purchase.


14 In both tags, the inductor couples to the RF magnetic field component parallel to the axis
15 of the coil within the hard tags or the surface normal of the label tags, as shown in Figure 1.
16 When placed onto a product this RF field component is therefore perpendicular to the material
17 onto which the tag is placed. When the material is conducting or polarizable, the perpendicular
18 RF field component generates eddy currents within the material that, due to Lenz’s law,
19 generate an opposing RF field that prevents efficient excitation of the tag. The cavity-based
20 tag presented in this work instead couples to the RF field component that lies within the plane
21 of the material onto which it is placed, and is immune to the formation of eddy currents within
22 the material. This design opens up the potential for discrete EAS tagging solutions for metallic
23 or polarizable materials that could be applied to hard, or deactivatable tagging applications. It
24 will be shown that the quarter-wavelength planar cavity can also be described by a simple LC -
25 resonator model that takes account of the geometrical features of the tag, and that the geometry
26 can be modified to yield the necessary values of L and C for operation at 8.2 MHz. The
27 dependence of the tag frequency and linewidth on the geometry and the properties of the ferrite
28 filling material are discussed, while finite element method modeling is used to reveal the

1 electromagnetic field profile within the cavity and the corresponding current distribution within
2 the metallic foil. Finally, the characteristics of the planar cavity tag, optimized for operation
3 on a conducting material at 8.2 MHz, are presented and compared to commercially available
4 adhesive label tags that are unable to operate on such materials.

6 **Tag details and experimental technique**

7 Prototype tags were formed from a closed-end cavity that consisted of a metal foil with
8 thickness of 50 μm wrapped around three surfaces of a ferrite slab, Figure 2(a). The NiZn high
9 frequency ferrite (MagDev F16), is specified by the manufacturer for application frequencies
10 between 0.5 and 10 MHz. Once the ferrite-filled part of the cavity was formed, a number, n ,
11 of additional foil wraps were made using the same strip of foil, as indicated by the block arrow
12 in Figure 2(a). To prevent electrical contact between the additional wraps and the foil of the
13 ferrite-filled part of the cavity, a separate polyethylene terephthalate (PET) dielectric film with
14 a thickness 25 μm , and width slightly larger than the foil, was inserted at the beginning of the
15 first additional wrap, Figure 2 (a-b). The dielectric film and metal foil were then wrapped about
16 the cavity concurrently to form the so-called ‘wrapped tag’, Figure 2(c). Wrapping in such a
17 way makes a top layer of foil on the dielectric film (shown as dashed layer in Figure 2(a))
18 redundant once wrapped back onto itself, and so it was omitted to simplify the tag construction,
19 yielding a structure similar to the metafilm described in reference [11]. The foil on either side
20 of the dielectric film forms an extension of the cavity with large capacitance, while the first foil
21 loop around the ferrite core has large inductance. The tag can either be described as an *LC*-
22 resonator [7, 11], or as a structured quarter-wavelength cavity with a substantial change of
23 cross-section along its length (similar to the half-wavelength cavity designs of reference [12]).

24 Tags were excited by a uniform radio-frequency (RF) magnetic field that was applied
25 perpendicular to the cross-sectional area of the cavity tag, or perpendicular to the planar spiral
26 inductor of label tags. The RF-field was generated by a single rectangular antenna loop that
27 mimicked those of security gates used to detect EAS tags in the doorways of retail stores, Figure
28 2(d). A vector network analyser (VNA) was used to drive a RF current around the loop with
29 an output power of 0 dBm and frequency swept in the range from 5 MHz to 50 MHz. The
30 frequency, linewidth, and absorption of the RF response of the tags was extracted from the
31 reflected power spectrum of the antenna loop recorded by the VNA, i.e. a single-port
32 measurement of the scattering matrix element S_{11} . When the RF frequency was swept through
33 the resonance frequency of the tag, a Lorentzian-shaped dip was observed in the power
34 spectrum of the antenna loop corresponding to the tag resonance.




1

2 Figure 2. (a) The unwrapped construction of the tag consists of a ferrite-filled foil cavity section of length
 3 l and thickness t and an additional cavity section that is filled with a thin dielectric spacer. Foil on top of
 4 the dielectric (dashed grey) becomes redundant once wrapped back onto the cavity and is therefore
 5 removed. (b) The wrapped tag consisting of the inductive ferrite-filled part of the cavity extended by a
 6 single capacitive wrap. (c) A cut-away schematic of the tag showing the width of the ferrite core w_f , and
 7 the cavity w_c . (d) Schematic of the single port vector network analyzer (VNA) set-up used to measure
 8 the tag absorption spectra as the frequency of the excitation magnetic field H_{RF} was swept. The tag was
 9 typically placed 2 cm from the plane of the antenna loop.

10

11 To demonstrate the problem of tagging metallic packaging using label tags, VNA
 12 measurements of the tag resonance spectrum were performed for tag-packaging separation
 13 ranging from 0 to 15 cm. Figure 3(b) shows that the tag should be separated by at least 5 cm
 14 from the packaging to recover the required frequency, linewidth, and absorption for normal
 15 operation, Figure 3(a-d). Spacing the tag by such a distance (greater than the tag lateral size)
 16 would be an undesirably bulky solution. Alternatively, the use of a high permeability ferrite
 17 block (MagDev F16 with initial $\mu_r \sim 100$, $l \times w_f \times t = 50 \times 30 \times 3 \text{ mm}^3$) between the tag and
 18 packaging can significantly reduce the tag detuning when closer than 5 cm, Figure 3(b-d).
 19 However, the high permeability modifies the tag inductance and detunes the tag to $\sim 6.6 \text{ MHz}$,
 20 and so the planar spiral inductor must be redesigned to compensate for the frequency shift when
 21 placed onto ferrite limiting the use of such tags to only metal packaging. Placing the ferrite
 22 backed label tag onto the metallic surface produces negligible absorption. Surprisingly, the
 23 absorption remains reduced compared to that of the free standing label tag even as the
 24 separation from the metal surface is increased. In contrast, the integration of the same ferrite
 25 block into the design of the wrapped cavity tag, and the addition of a thin metallic shield to the
 26 outside of the tag, leads to a more effective solution for a universal tag that can be used on

1 metallic, and non-metallic packaging. It will be shown that such a wrapped tag exhibits greater
 2 absorption on metal to that of the label tag in free space.



3
 4 Figure 3. (a) VNA spectra acquired for the label tag only (in free space) when placed between 0 and 5 cm from
 5 the surface of metallic packaging. The tag was placed at the centre of the antenna loop in a plane parallel to
 6 that of the packaging surface. The packaging was then moved away from the tag to generate the separation.
 7 The tag frequency (b), linewidth (c), and absorption (d) are shown as a function of separation from the
 8 packaging. In (b) to (d) the open black squares correspond to the data in (a) that was acquired for the tag
 9 surrounded only by air, while open red circles correspond to the case when a high permeability ferrite was
 10 placed on the tag between the tag and the packaging.

11

12 Analytical model

13 The frequency of the tag may be predicted using a simple analytical model based on the
 14 geometry of the ferrite-filled foil cavity and the number n of additional dielectric-foil wraps.
 15 Since the total area, and therefore capacitance, of the additional wraps is approximately
 16 proportional to n , the frequency changes in accordance with that expected of an LC resonator
 17 with frequency given by

$$18 \quad f = \frac{1}{2\pi\sqrt{LC_n}} \frac{1}{\sqrt{n}}, \quad \text{Equation (1)}$$

19 where C_n is the capacitance per additional wrap. The inductance of the cavity is estimated by
 20 treating it as a parallel plate waveguide [13] since the cavity length l is much greater than its
 21 thickness t , *i.e.* $l \gg t$. The magnetic field is assumed to be spatially uniform within the cavity,
 22 and parallel to both the plane of the cavity and to its width w_c . By considering an Ampèrian

1 loop with one arm inside and one arm outside the cavity (perpendicular to the uniform current
 2 flow along the plate length l) the inductance of the cavity is [13]

$$3 \quad L = \frac{\mu_0 \mu_r l t}{w_c}, \quad \text{Equation (2)}$$

4 where μ_0 and μ_r are the permeability of free space and the relative permeability of the ferrite
 5 material respectively, and the smaller inductance due to the dielectric-filled section is neglected.

6 The capacitance may be estimated from the approximate total area of the additional
 7 wraps and the thickness of the dielectric film and is given by

$$8 \quad C_n = \frac{2\varepsilon_0 \varepsilon_r n w_c (l+t)}{d}, \quad \text{Equation (3)}$$

9 where ε_0 , ε_r , are the permittivity of free space and the relative permittivity of the dielectric,
 10 $2w_c(l+t)$ is the approximate area of each additional wrap (see Figure 2(c)), d is the thickness
 11 of the dielectric, and the smaller capacitance of the ferrite-filled section is neglected. Assuming
 12 that there are no air gaps present between the dielectric film and the metal foil, the frequency
 13 of the tag

$$14 \quad f = \frac{1}{2\pi} \sqrt{\frac{d}{2\varepsilon_0 \varepsilon_r \mu_0 \mu_r n l t (l+t)}}, \quad \text{Equation (4)}$$

15 is then seen to be independent of the cavity width w_c within the model. The relative permittivity
 16 of the dielectric film (Melinex) is assumed to have a frequency independent value of 3.[14]
 17 The inductance of the tag in equation (2) may be rewritten as

$$18 \quad L = \frac{d}{8\pi^2 \varepsilon_0 \varepsilon_r \xi^2 (l+t) w_c}, \quad \text{Equation (5)}$$


19 where $\xi = f\sqrt{n}$. Equation 5 therefore allows the inductance of the tag to be determined
 20 without the need to determine the relative permeability.

21

22 **Results and Discussion**

23 The resonant frequency of the cavity is dependent on the cross-sectional area of the
 24 inductive foil loop and the permeability of the ferrite filling material. In practice there is also a
 25 weaker dependence on the cavity width [1]. The frequency of the tag can be further tuned via
 26 the number of additional capacitive dielectric/foil wraps. Starting with $n = 10$ wraps, the wraps
 27 were then cut away from the tag in 0.5 wrap steps and the resonant frequency recorded. In this
 28 study, the dimensions of the ferrite core (see Figure 1(c)) were $l = 50$ mm, $w_f = 30$ mm, and $t =$
 29 1.3 mm. The width of both the foil cavity and subsequent dielectric/foil wraps was $w_c = w_f =$

1 30 mm, i.e. the cavity, wraps, and ferrite core had the same nominal width. The thicknesses of
 2 the metal foil and dielectric film were $50\ \mu\text{m}$ and $d = 25\ \mu\text{m}$ respectively. For this geometry,
 3 Equation 3 yields a capacitance of $C_1 \approx 3.3\ \text{nF}$ for a single ($n = 1$) wrap. Figure 4(a) shows
 4 typical absorption spectra (grey spectra) acquired for a tag with n complete additional wraps
 5 for $n = 1, 2, 3, 4$. Fitted Lorentzian peaks are overlaid (black line). A background spectrum
 6 with a weak frequency dependence (not shown) was acquired and subtracted from each tag
 7 spectrum before peak fitting. The resulting spectra shown in Figure 2(a) are offset by 0.1 dB
 8 for clarity.



9

10 Figure 4. (a) The absorption spectra of tags with additional number of wraps $n = 1, 2, 3,$ and 4 . The
 11 measured spectra (light grey) are overlaid by fitted Lorentzian peaks from which the frequency,
 12 linewidth, and absorption are extracted. The spectra are offset by 0.1 dB for clarity. (b) The extracted
 13 frequencies of tags with $n = 0.5$ to 9.5 . The linear fit as a function of $n^{-1/2}$ confirms that the additional
 14 wraps add capacitance, but do not significantly affect the inductance. The modelled curves (overlaid red
 15 and blue) show the frequencies calculated from the geometry of the tags and the ferrite permeability
 16 obtained from the manufacturer (blue dashed curve) and from permeammeter measurements [2] (red
 17 dotted curve).

18

19 As the number of wraps was decreased from 4 to 1, the frequency rapidly increased by a factor
 20 of 2 from 15 MHz to 30 MHz, in accordance with a $n^{-1/2}$ dependence. As the number of wraps


1 was increased the frequency approached ~ 10.5 MHz, outside of the detection range for EAS at
2 8.2 MHz. The linear fit of Figure 4(b) confirmed the $n^{-1/2}$ frequency dependence of the tag.
3 The linear dependence of frequency on $n^{-1/2}$ indicates that the frequency is tuned primarily by
4 the change in capacitance of the tag with each additional wrap. This suggests that the ferrite-
5 filled part of the cavity provides practically all of the tag inductance. The self-inductance of the
6 additional wraps makes little contribution since both t and μ_t (in Equation 2) are approximately
7 two orders of magnitude smaller in the wrapped part of the cavity compared to their values in
8 the ferrite-filled part.

9 The analytical model (Equation 4) can be used to model the experimental data with each
10 additional layer being assumed to have the capacitance given by Equation 3. The frequency
11 dependence of the real part of the complex permeability of the ferrite was also included. The
12 permeability data was obtained from the manufacturer, but was also extracted from
13 permeammeter measurements performed on rectangular blocks, similar to those described in
14 reference [15]. The modeled dependence of the tag frequency on $n^{-1/2}$ using the permeability
15 data from the manufacturer and the permeammeter are shown as blue dashed and red dotted
16 curves respectively. The curves were calculated by solving Equation 4 for n since the frequency
17 dependent real part of the permeability is known. The model that assumed the manufacturer's
18 permeability data is in good agreement with the experimental data for $n \geq 1$. However, when
19 $n < 1$, *i.e.* a half wrap, the model predicts a significantly larger frequency than is observed in
20 the experiment. A similar upturn in frequency is also predicted by the model that assumes the
21 permeability values acquired from the permeammeter. The upturn could be attributed to an
22 underestimate of either the capacitance or inductance of the tag when the first additional wrap
23 is incomplete. The difference between the experimental data and the modeled data calculated
24 using the real part of the permeability extracted from permeammeter measurements is observed
25 over the entire range of n , in Figure 3(b). This is due to the known underestimate of the
26 permeability, due to small air gaps where the RF magnetic flux is high in the permeammeter,
27 which reduces the effective permeability obtained in this measurement. In contrast the
28 manufacturer's values are obtained from toroidal specimens for which air gaps are eliminated.

29 The microwave absorption and spectral linewidth of the tag are also sensitive to the
30 cavity dimensions and the number of additional wraps. The amplitude of the microwave
31 absorption is proportional to the cross-sectional area of the ferrite-filled cavity. However, the
32 absorption and linewidth are also sensitive to the frequency dependent loss associated with the
33 ferrite filling material. For example, Figure 4(a) shows that higher frequency tags with a single
34 wrap ($n = 1$) exhibit enhanced linewidth and reduced amplitude in contrast to lower frequency
35 tags with ($n = 2, 3$, and 4). Figure 5(a) summarizes the frequency dependence of the resonance
36 linewidth and quality factor (Q -factor = frequency/linewidth) of the tags as n is reduced from

1 9.5 to 0.5 in half-wrap increments. Between 10 MHz and 42 MHz the linewidth increases by
 2 approximately one order of magnitude, while at 42 MHz the Q -factor decreases to
 3 approximately one third of its peak value observed at ~ 20 MHz.

4 The ferrite filling material is required to have a large real part of the permeability ($\text{Re}(\mu_r)$)
 5 and low magnetic loss ($\text{Im}(\mu_r)$) in order to yield a tag with low frequency and high Q
 6 resonances. However, for the dielectric thickness of $25 \mu\text{m}$ and the range of n used for the
 7 prototype tags, the resonance frequency of the tags exceeds that at which it can be assumed that
 8 the real part is constant, and the imaginary part is small. The frequency dependence of the
 9 linewidth and Q -factor can then be understood from the dispersion of the



10
 11 Figure 5. (a) The linewidth (LW) and Q -factor extracted from the measured absorption spectra for tags
 12 with number of turns, $n = 0.5$ to 9.5 , plotted as a function of frequency. (b) The real and imaginary
 13 components of the complex permeability extracted from permeammeter measurements of the F16 ferrite
 14 filling material as a function of frequency. The peak in $\text{Re}(\mu_r)$ is seen to coincide with the increase of
 15 $\text{Im}(\mu_r)$. The increase of $\text{Im}(\mu_r)$ also coincides with the enhanced linewidth and reduced Q -factor in (a),
 16 indicating that magnetic losses in the ferrite core of the tag become significant above 25 MHz.

17
 18 permeability μ_r of the ferrite filling material (Figure 5(b)), determined from the
 19 permeammeter measurements. The frequency dependence of $\text{Re}(\mu_r)$ and $\text{Im}(\mu_r)$ has the
 20 typical character described by Snoek [16, 17]. The measured value of $\text{Re}(\mu_r)$ at 10 MHz

1 is ~ 90 and is sufficient to realize a tag with size and frequency required for EAS at 8.2
2 MHz. With increasing frequency, the value of $\text{Re}(\mu_r)$ increases to a peak of ~ 110 at 35
3 MHz, Figure 5(a), before falling. In contrast the value of $\text{Im}(\mu_r)$ at 10 MHz determined
4 from the permeammeter measurements is ~ 1 and remains small until the frequency
5 increases to ~ 20 MHz after which it increases to a peak value ~ 55 at 65 MHz, Figure
6 5(a). It is clear from Figure 5(a) and Figure 5(b) that the increase in linewidth and
7 decrease in Q-factor are correlated with the increase in the imaginary component of the
8 ferrite permeability corresponding to magnetic losses [3,4]. An increasing number of
9 wraps ($n > 2$) allows the frequency of the tag to be tuned into the low loss regime where
10 $\text{Re}(\mu_r)$ is large. Such tunability is essential to achieve the frequency, Q-factor, and
11 signal amplitude required for detection by EAS gate systems. At the same time, the
12 increased inductance of the ferrite-filled tag allows the lateral dimensions of the tag to
13 be reduced to $3 \times 5 \text{ cm}^2$: a small reduction in area compared to label tags that have
14 adopted a standard size of $4 \times 4 \text{ cm}^2$ [5].

15 To further confirm that the ferrite-filled section of the cavity provides the
16 dominant contribution to the self-inductance of the structure, ceramic capacitors were
17 electrically connected to the open end of only the ferrite filled part of the cavity. The
18 range of capacitance of the ceramic capacitors ($1 < C < 7 \text{ nF}$) was chosen to be similar
19 to that calculated for two wraps of dielectric and foil. In accordance with equation 1, a
20 linear fit of frequency, f versus $(nC_n)^{-1/2}$ (not shown) allowed a cavity inductance of
21 42.4 nH to be calculated. Here C_n and n can be considered as the capacitance of each
22 ceramic capacitor and the number of capacitors added, respectively. A similar analysis
23 can be applied to the wrapped tag. However, it is necessary to estimate the capacitance
24 of each wrap from its geometry. The gradient ξ of the linear fit to f versus $n^{-1/2}$ in Figure
25 4(b) allowed the inductance to be estimated using Equation 5. The inductance of the
26 wrapped tag was calculated to be 9.4 nH, slightly less than 1/4 of that determined for
27 the cavity by using ceramic capacitors, and so the additional wraps do not appear to
28 enhance the inductance. Instead this suggests that the model based on the geometry of
29 the wraps overestimates the value of the total capacitance. This is associated with
30 imperfect wrapping of the separate metal foil and dielectric film, leading to small gaps
31 between the metal and dielectric that fill with air with relative permittivity $\epsilon_r \sim 1$. Indeed,
32 compressing the tag firmly between fingers was found to yield a further decrease in
33 frequency consistent with enhancement of the capacitance through local removal of air

1 gaps. To consistently minimize the influence of air gaps a firm tension was applied to
2 the additional foil/dielectric warps while wrapping. The capacitance of two parallel
3 plates, separated by a layer of dielectric of thickness d and relative permittivity ϵ_r , and
4 air gap of thickness d_g , can be written as

$$5 \quad C = \frac{\epsilon_0 A}{\left(d_g + \frac{d}{\epsilon_r}\right)}, \quad \text{Equation (6)}$$


6 where A is the area of the capacitor. Therefore, an air gap with thickness equal to the
7 dielectric thickness ($d_g = d$) reduces the capacitance by a factor $\left(\epsilon_r \frac{d_g}{d} + 1\right)^{-1}$. If $\epsilon_r =$
8 3, the capacitance may be reduced by a factor of 1/4 if $d_g = d$. The resulting
9 overestimate of the wrap capacitance then leads to an underestimate of the inductance.
10 Despite the best efforts to eliminate air gaps between the separate dielectric film and
11 metal foil, their presence could be seen and a gap thickness of $\sim d$ seems very reasonable.
12 Therefore, the presence of air gaps is the most plausible explanation for the observed
13 discrepancy in the tag inductance. In demonstration tags for retail trials discussed later
14 in this article, the consistency of tag manufacture was improved by vacuum sealing the
15 tags to remove all air gaps. However, for the present study of the tag response as a
16 function of the number of turns it was not practical to vacuum seal the tag for each half
17 wrap increment.

18

19 **Finite element modelling**

20 In order to gain further insight into the electromagnetic field distribution within
21 the tag, finite element method (FEM) modeling was used to understand the current
22 distribution in the foil of the cavity and additional wraps. The previously stated
23 dimensions of the ferrite core length and thickness, foil and dielectric thickness, and
24 number of additional wraps were assumed, while the frequency dependent complex
25 permeability values obtained from the permeammeter measurements were used. The
26 model assumed an infinitely wide cavity, *i.e.* $w_f = w_c \rightarrow \infty$. In a simplified approach,
27 the metal foil was assumed to be a perfect electrical conductor (PEC) and eigenmode
28 solutions of the quarter-wavelength TEM mode were obtained for a tag with number of
29 wraps $n = 1$ and $n = 2$. Meshing within the microscale thickness of the foil and dielectric
30 is computationally challenging due to the centimeter length scale of the cavity. If the

1 metal is not treated as a PEC then meshing within the metal foil, to account for the skin
 2 depth, can lead to a reduction of the resonance frequency of a cavity TEM mode [18].
 3 Figure 6 shows x - y cross-sections of the electromagnetic field distributions taken across
 4 the width and midway along the length of a tag with number of wraps $n = 1$. For clarity,
 5 the field distributions are only shown at ± 1 mm from the center of the tag (i.e., from
 6 $l/2$) along y . The current direction and density are represented by black arrows on the
 7 surfaces of the PEC foil.



8

9 Figure 6. Finite element modelling (FEM) of tags for $n = 1$ and modelled frequency of 4.57 MHz. Plots
 10 in (b) and (c) have been extracted from a finite width cross-section in the xy plane close to the center of
 11 the tag length, as indicated in the schematic in (a), not to scale. In (b) the amplitude of the x -component
 12 of the electric field is shown in accordance with the color scale (in Vm^{-1}). Regions of large electric field
 13 amplitude are confirmed to lie within the thin dielectric film of the capacitive wraps. In (c) the amplitude
 14 of the z -component of the magnetic field is shown in accordance with the color scale (in A/m). Regions
 15 of large magnetic field are confirmed to lie within the ferrite core, but are also found within the dielectric
 16 of the additional wraps. In (b) and (c) the direction and density of current on the surface of the PEC is
 17 indicated by the direction and length of the arrows.


18

19 The decrease in frequency of the modelled tag when n is increased from 1 to 2
 20 wraps is in agreement with the experiment. However, the values of the modeled
 21 frequencies (4.57 MHz for $n = 1$, and 3.77 MHz for $n = 2$) do not agree with those of
 22 the experiment (~ 30 MHz for $n = 1$, and ~ 20 MHz for $n = 2$). The discrepancy is
 23 expected and is due to the assumption of an infinitely wide cavity [9]. For a cavity of
 24 infinite width, the magnetic field generated by the electric current distribution is
 25 confined to the ferrite core with large relative permeability. However, for a cavity of
 26 finite width, the magnetic field also extends outside the core into free space surrounding

1 the cavity where the relative permeability is unity. The volume averaged permeability,
2 seen by the internal magnetic field within the core and the stray field outside the tag, is
3 significantly reduced with respect to the permeability of the ferrite, leading to a
4 reduction of the self-inductance, and therefore a higher frequency as observed in the
5 experiments.

6 Despite the quantitative discrepancy, the model indicates that the current flows in
7 opposite directions on successive dielectric/foil interfaces of the wrapped cavity
8 structure. The current flow on the surfaces of the wrapped metal foil is readily
9 understood from the unwrapped picture of the cavity in Figure 1(a) where current in the
10 foil on opposite sides of the dielectric flows in opposite directions. A magnetic field
11 antinode is observed where maximum current flow occurs, in accordance with
12 Ampère's law (Figure 6(c)). Figure 6(b) confirms that the amplitude of the E_x
13 component is largest in the capacitive part of the cavity where the foil is separated by
14 the thin dielectric film, and in fact is maximum at the open end of the cavity, neglecting
15 fringing effects [9]. Since the capacitive part of the cavity is wrapped around the core,
16 the sign of E_x is opposite on opposite sides of the cavity, as indicated by red and blue
17 E_x contrast in Figure 6(b). A movie of the alternating current and field distributions is
18 provided in the Supplementary Material for a tag with modified dimensions for the
19 purposes of demonstration. Further experimental and FEM investigations are now
20 required to understand the current distribution within metal foils with thickness
21 comparable to the skin depth.

22 Profiles of the z -component of magnetic field within the ferrite (shaded yellow)
23 and the dielectric regions of the animated tag[19] are shown Figure 7(a). The profiles
24 were extracted along the dashed line section A-A' in Figure 7(b). The profiles indicate
25 a linear decrease of the magnetic field amplitude along the length of the dielectric filled
26 section, but almost constant amplitude within the ferrite. In contrast the electric field
27 amplitude is approximately constant within the dielectric-filled section before
28 decreasing monotonically into the ferrite-filled section.




1

2 Figure 7. (a) The time-averaged magnitude of the electric field (blue solid curve) and magnetic field (red
 3 dashed curve) are shown as a function of position along the length of the tag cavity, extracted from the
 4 dashed line section A-A' in (b). The section passes along the length of the ferrite filled part of the cavity
 5 (0 to 5 mm shaded yellow in (a) and (b)) before wrapping around into the dielectric filled part of the
 6 cavity. The profiles are extracted from the modelled animation in the supplementary material.

7

8 **Prototype EAS tags**

9 While the tags considered so far have allowed the underlying physics to be
 10 understood, their resonance frequency was consistently too high for EAS applications.
 11 Furthermore, the Q -factor and signal amplitude compare unfavorably with those of
 12 existing EAS tags, and do not provide the signal quality required to trigger an EAS gate
 13 system. To reduce the frequency to 8.2 MHz it is necessary to increase the capacitance
 14 by reducing the dielectric thickness and eliminating air gaps where possible. At the
 15 same time the Q -factor and signal strength can be enhanced by reducing the cavity
 16 width with respect to that of the ferrite core, i.e. making $w_c < w_f$, in accordance with
 17 previous work [9].



1

2 Figure 8. (a) Measured absorption spectra for tags with $n = 1$ constructed with $40 \mu\text{m}$, $30 \mu\text{m}$, and $20 \mu\text{m}$
 3 foil thickness with triple ($m = 3$), double ($m = 2$), and single ($m = 1$) layer applications of heat-seal lacquer
 4 (black, red, and blue curves respectively). Only a single layer of lacquer was applied to the $10 \mu\text{m}$ thick
 5 foil. (b) Measured absorption spectra for a proof of concept wrapped tag with $n = 2$ when placed on
 6 stainless steel (blue curve) and cardboard (black curve) packaging. The spectrum for an EAS industry
 7 standard $40 \times 40 \text{ mm}^2$ label tag is shown (shaded grey) in addition to the frequency band of EAS
 8 detection gates (shaded yellow).

9

10 To enhance the capacitance a vinyl-based heat-seal lacquer was used as the
 11 dielectric layer. While the precise composition was unknown, heat-seal lacquers
 12 typically contain polyvinyl-chloride (PVC), which has a dielectric constant of ~ 3.4 and
 13 is similar to that of the PET film used so far. Single ($m = 1$), double ($m = 2$), and tri-
 14 layers ($m = 3$) of lacquer were rolled onto foils of thickness $40 \mu\text{m}$, $30 \mu\text{m}$, and $20 \mu\text{m}$.
 15 For a foil thickness of $10 \mu\text{m}$, only a single layer of lacquer was applied. One advantage
 16 of laminating one side of the foil with lacquer is the elimination of air gaps between
 17 one of the two dielectric/foil interfaces within the capacitive part of the tag.

18 Tags with foil/lacquer laminates were made using an F16 ferrite core with
 19 $l = 48 \text{ mm}$, $w_f = 30 \text{ mm}$, and $t = 1.5 \text{ mm}$ (a slightly shorter and thicker core than used

1 previously). Each laminate strip was wrapped around the core to form the cavity and
2 only one complete wrap. The width of the strip lacquer and foil are necessarily equal.
3 Electrical contact between the cavity and the single additional wrap at the edges of a
4 strip of uniform width can short circuit the capacitive wrap. To prevent this, laminate
5 strips initially 30 cm long, were tapered from approximately 2 cm wide at one end, to
6 1 cm wide at the other. This ensured that the lacquer provided electrical isolation of
7 the foil edges of the ferrite-filled part of the cavity from those of the wrapped part of
8 the cavity.

9 The absorption spectra for tags made with laminate strips of different foil and
10 lacquer thickness are shown in Figure 8(a). In general the tag frequency decreased as
11 the lacquer thickness was reduced. This is clear for a foil thickness of 20 μm and 40
12 μm , but for the 30 μm thick foil the decrease was non-monotonic and ascribed to
13 imperfect reproducibility of cutting and wrapping of the laminate by hand. The tag
14 frequency can also be seen to decrease as the metal foil thickness was reduced. This is
15 most clearly observed for two layers of lacquer ($m = 2$), while triple and single layers
16 of lacquer showed slight deviations from this trend. The reduction in frequency for tri-,
17 double, and single layers of lacquer was most significant for tags with a laminate foil
18 thickness of 40 μm . The measured tag frequencies were used to estimate the lacquer
19 thickness, (equation 4) by comparing the frequency of a tag with one additional wrap
20 ($n = 1$) of foil(40 μm)/lacquer laminate to that of such a tag constructed with one
21 additional wrap of separate metal foil and dielectric film, see Figure 2(a). It was
22 assumed that the dielectric constant of PET and PVC were ~ 3 and ~ 3.4 respectively.
23 Differences in the ferrite core dimensions were accounted for, in addition to the
24 different value of the core permeability at the different tag frequencies. The thickness
25 of a single, double, and tri-layer of heat-seal vinyl lacquer was estimated to be 3.4 μm ,
26 4.9 μm , and 6.6 μm respectively.

27 The irregular change in frequency with decreasing lacquer thickness for the
28 30 μm foils, and for decreasing metal thickness for the single and triple layer lacquer,
29 is ascribed to the difficulty of hand-wrapping thin laminates, i.e., ensuring that the wrap
30 is tight while avoiding damage to the thin dielectric lacquer, foil, or both. Air gaps
31 between the exposed surfaces of the lacquer and the foil of the cavity could not be

1 eliminated completely and are known to affect the observed frequencies by reducing
2 the capacitance of the wrap.

3 The most effective reduction of frequency to a value close to 8.2 MHz was
4 achieved using 20 μm and 10 μm thick foils and a single layer of lacquer for which tag
5 frequencies of ~ 8.94 MHz and 9.54 MHz were achieved respectively. The slightly
6 higher tag frequency achieved with the 10 μm thick foil was again ascribed to air gaps,
7 since this delicate laminate could not be wrapped tightly. To assist with the elimination
8 of such air gaps, the tag was vacuum secured by heat-sealing inside a plastic pocket.
9 This allowed the capacitance to be optimized and the frequency reduced to below
10 8.2 MHz. A small amount of air was then allowed back into the bag via a small
11 puncture hole to reduce the capacitance and increase the tag frequency. This process
12 was carried out with the tag placed onto stainless steel packaging, while the frequency
13 of the tag was monitored *in-situ* as the air flowed back between the cavity and the single
14 additional wrap to achieve a frequency close to 8.2 MHz, Figure 8(b) blue curve. The
15 puncture was then sealed with adhesive tape and the vacuum pocket heat sealed again
16 to prevent the puncture from leaking further. The tag frequency was 8.36 MHz, slightly
17 higher than the preferred 8.2 MHz. However, the EAS gate systems have a detection
18 frequency band from 7.6 MHz to 8.7 MHz (Figure 8(b), yellow band). In fact, when
19 the tag was placed on non-metallic packaging such as cardboard, the detuning from
20 8.36 MHz to 8.12 MHz (Figure 8(b) black curve) was sufficiently small that the tag
21 frequency remained within the detection band of the gate[20]

22 To assess the viability of the wrapped planar tag as an EAS solution for metallic
23 packaging it should perform to a similar standard to existing EAS tags. For comparison,
24 the spectrum of the standard EAS label tag, with frequency of 8.14 MHz measured in
25 free space, is also shown in Figure 8(b), shaded grey. The wrapped planar cavity tag
26 exhibited reduced absorption, increased linewidth, and reduced Q -factor, with respect
27 to the standard tag, Table 1. To prevent the linewidth from becoming too large,
28 particularly for packaging containing ferrous material, the wrapped planar tags were
29 integrated with an Al foil shield. The shield had a thickness of at least one skin depth
30 (~ 30 μm) at 8.2 MHz and an area of $\sim 50 \times 50$ mm^2 and could either be contained within
31 the heat-sealed vacuum pocket, or attached with adhesive to the outside of the pocket.
32 The shield helps to prevent magnetic losses within ferrous metallic packaging, e.g.,

1 magnetization reorientation and domain wall motion, driven by the RF magnetic field
 2 associated with the tag.

	Wrapped tag		Standard tag
	Stainless steel	Cardboard	Air
Frequency (MHz)	8.36	8.12	8.14
Linewidth (MHz)	0.19	0.15	0.12
Q-factor	43	54	66
Peak absorption (dB)	-0.19	-0.13	-0.31
Read distance (cm)	80	80	90

3 Table 1. Wrapped tag characteristics extracted from measured absorption spectra of Figure 8(b) for a
 4 vacuum sealed, proof of concept wrapped tag with $n = 2$ when placed on stainless steel and cardboard
 5 packaging. The characteristics for an EAS industry standard $40 \times 40 \text{ mm}^2$ label tag are also shown.


6

7 The cross-sectional area of the planar spiral inductor coil of the standard tag
 8 ($\sim 1600 \text{ mm}^2$) exceeds that of the inductive part of the wrapped tag ($\sim 72 \text{ mm}^2$) by more
 9 than 20 times. Despite this, the enhanced inductance of the cavity, due to the high
 10 $\text{Re}(\mu_r)$ ferrite core, leads to an absorption that is $\sim 40\%$ to $\sim 60\%$ that of the standard tag
 11 absorption, which allows the wrapped tag to effectively couple to the EAS detection
 12 gate. Furthermore, the absorption of the wrapped tag was enhanced when the tag was
 13 placed on stainless steel instead of cardboard. One tentative explanation is that the in-
 14 plane component of the RF magnetic field generated by the EAS detection gate is
 15 enhanced in the vicinity of metallic packaging, which helps it to couple to the tag.

16 To confirm the reproducibility and assess the viability of the hand-made
 17 wrapped tags, a small batch were made in anticipation of retail trials. To enhance the
 18 coupling to EAS detection gates the ferrite core thickness was increased to 3 mm.
 19 Laminate strips with composition Al(18 μm)/vinyl lacquer(3 g/m^2) were cut by
 20 Multifoil Ltd.¹ in reproducible batches. The strips had initial length of 30 cm, and were
 21 tapered from 2 cm at one end, to 1 cm at the other. Of 45 tags constructed and vacuum
 22 sealed in the way described previously, 37 tags exhibited frequencies between 8 MHz
 23 and 8.4 MHz at the end of their construction. Figure 9 shows exemplar absorption

¹ 24 Marsh Green Road West, Marsh Barton, Exeter, EX2 8LZ

1 spectra acquired during the construction of a tag. Initially, the heat-sealed vacuum
2 enclosure reduced the tag frequency to 5.5 MHz in free space, and 6.8 MHz on stainless
3 steel as the air is removed from the capacitive part of the tag.



4
5 Figure 9. Absorption spectra measured during the construction of a wrapped tag for retail trial. Spectra
6 acquired for the tag in free space, and on stainless steel packaging, are shown as blue and black curves
7 respectively. The spectrum for the EAS industry standard $40 \times 40 \text{ mm}^2$ label tag is also shown (red
8 curve). Note that the label tag is not shielded, but shown for comparison only. The top two 'vacuum
9 sealed' spectra were acquired after the ferrite and wrapped foil/lacquer laminate strip were heat-sealed
10 in a vacuum pocket. The middle two 'tuned' spectra were acquired after the vacuum was punctured, the
11 tag tuned to ~ 8.2 MHz on stainless steel packaging, and then heat sealed once again. The bottom
12 'shielded' spectra were acquired after a $50 \times 50 \text{ mm}^2$, $50 \mu\text{m}$ thick, Al foil shield was attached to the
13 packaging side of the tag.

14
15 Once the tag was tuned to approximately 8.2 MHz on stainless steel, there is a
16 significant difference between the tag frequency on stainless steel (8.2 MHz) and in
17 free space (6.6 MHz). The addition of an Al foil shield to one side of the tag
18 permanently mimics the presence of non-ferrous metallic packaging so that the tag
19 frequency in free space (8.1 MHz) and on non-magnetic stainless steel (8.4 MHz) are
20 more similar to each other, are both within the detection frequency band of EAS gates,
21 and both similar to the industry standard EAS 40 mm label tag (8.3 MHz in Figure 9).
22 When the wrapped tag is placed onto metal packaging its absorption exceeds that of the
23 label tag in free space, demonstrating that it makes more effective use of the ferrite
24 block, than simply placing the label tag onto the ferrite, as shown in Figure 3(d).

1

	Mean	Standard deviation	Minimum	Maximum
Frequency (MHz)	8.16	0.0760	8.01	8.28
Linewidth (MHz)	0.211	0.0552	0.116	0.296
Q-factor	41.8	12.6	27.3	69.9
Peak absorption (dB)	-0.151	0.0458	-0.241	-0.0923
Read distance* (cm)	83.3	7.76	70.0	90.0

2 Table 2. Average wrapped tag characteristics extracted from measured absorption spectra for 37 vacuum
3 sealed, proof of concept wrapped tags with $n = 2$ when placed on stainless steel packaging.

4 *For 35 of 37 tags only, measured along the center-to-center line of an EAS security gate to the position
5 at which a tag triggers the gate.

6

7 The mean frequency, linewidth, Q -factor, peak absorption, and read distance
8 are provided in Table 2, in addition to their standard deviation and minimum and
9 maximum values. The good reproducibility of this small batch of tags demonstrates
10 that there is potential for larger scale manufacture of the wrapped tags for EAS solutions
11 for metallic packaging. Of particular note is the narrow range of frequencies that lie
12 well within the EAS detection range, and the variation in read distance, which
13 approaches the desired distance for EAS detectors placed to either side of the exit within
14 a retail store.

15

16 **Summary**

17 In summary, planar quarter-wavelength cavities have been adapted to develop an
18 EAS tag solution for metallic packaging. The tag can be described as a quarter-
19 wavelength cavity with an impedance mismatch part-way along its length, between a
20 section containing a high permeability ferrite filling material, and another section
21 containing a thin dielectric filling material. Alternatively, the same two sections can be
22 thought of as contributing the lumped inductance and capacitance, respectively, of an
23 LC -resonator. These models of the tag have allowed the current distribution flowing
24 through the wrapped foil, and the inductive and capacitive contributions to the
25 impedance to be understood. This understanding has allowed working prototypes to be

1 demonstrated in small batches with well-reproduced characteristics such as frequency
2 and linewidth, which make them viable solutions to the problem of tagging metallic
3 packaging within the EAS industry.

4

5 **Acknowledgements**

6 The authors gratefully acknowledge the financial support of the UK
7 Engineering and Physical Sciences Research Council via grants EP/L015331/1 (Centre
8 for Doctoral Training in Metamaterials, E.G.), EP/I500219/1 (A planar microwave
9 cavity loaded with ferrromagnetic material: a new 8.2 MHz anti-theft tag for metallic
10 packaging within the retail sector), and EP/R004781/1 (EPSRC and QinetiQ Ltd. via
11 the TEAM-A prosperity partnership, I.R.H.). The authors make special thanks to Andy
12 Hayling of MagDev Ltd. for the provision of custom ferrite cores, and Mike Cochran
13 of Crown Packaging PLC. for the provision of prototype aluminum foil/vinyl lacquer
14 laminates.

15 Open access to supporting research data is provided by Open Research Exeter
16 at <http://hdl.handle.net>

17

18 **References**

- 19 1. Liberal, I., A.M. Mahmoud, and N. Engheta, *Geometry-invariant resonant cavities*. Nature
20 Communications, 2016. **7**: p. 10989.
- 21 2. Gold, S.H. and G.S. Nusinovich, *Review of high-power microwave source research*.
22 Review of Scientific Instruments, 1997. **68**(11): p. 3945-3974.
- 23 3. Stern, I., et al., *Cavity design for high-frequency axion dark matter detectors*. Review of
24 Scientific Instruments, 2015. **86**(12): p. 123305.
- 25 4. Alici, K.B., et al., *Experimental verification of metamaterial based subwavelength*
26 *microwave absorbers*. Journal of Applied Physics, 2010. **108**(8): p. 083113.
- 27 5. R. E. Collin, *Field Theory of Guided Waves*, 2nd ed. (Wiley-IEEE Press, 1990).
- 28 6. Porto, J.A., F.J. García-Vidal, and J.B. Pendry, *Transmission Resonances on Metallic*
29 *Gratings with Very Narrow Slits*. Physical Review Letters, 1999. **83**(14): p. 2845-2848.

- 1 7. Sievenpiper, D., et al., *High-impedance electromagnetic surfaces with a forbidden*
2 *frequency band*. Microwave Theory and Techniques, IEEE Transactions on, 1999. **47**(11):
3 p. 2059.
- 4 8. Zhao, B. and Z.M. Zhang, *Study of magnetic polaritons in deep gratings for thermal*
5 *emission control*. Journal of Quantitative Spectroscopy and Radiative Transfer, 2014. **135**:
6 p. 81-89.
- 7 9. Keatley, P.S., et al., *Ferrite-filled cavities for compact planar resonators*. Applied Physics
8 Letters, 2014. **104**(2): p. 022405.
- 9 10. H. Imaichi; T. Matsumoto; Y. Suzuki; K. Himura; T. Haneda, *Resonant tag and method*
10 *of manufacturing the same*, United States Patent 5,447,779 (1995).
- 11 11. Acher, O., *Permeability enhancement of soft magnetic films through metamaterial*
12 *structures*. Journal of Magnetism and Magnetic Materials, 2008. **320**(23): p. 3276-3281.
- 13 12. Lockyear, M.J., A.P. Hibbins, and J.R. Sambles, *Transmission of microwaves through a*
14 *stepped subwavelength slit*. Applied Physics Letters, 2007. **91**(25): p. 251106.
- 15 13. Ramo, S., Whinnery, J.R. and van Duzer, T. (1994) *Fields and Waves in Communication*
16 *Electronics*. John Wiley & Sons, Inc., New York.
- 17 14. Svorčák, V., et al., *Permittivity of polyethylene and polyethyleneterephthalate*. Journal of
18 *Materials Science Letters*, 2000. **19**(20): p. 1843-1845.
- 19 15. Barry, W., *A Broad-Band, Automated, Stripline Technique for the Simultaneous*
20 *Measurement of Complex Permittivity and Permeability*. Microwave Theory and
21 *Techniques*, IEEE Transactions on, 1986. **34**(1): p. 80-84.
- 22 16. Snoek, J.L., *Gyromagnetic resonance in ferrites*. Nature, 1947. **160**(4055): p. 90-90.
- 23 17. Snoek, J.L., *Dispersion and absorption in magnetic ferrites at frequencies above one MC/s*.
24 *Physica*, 1948. **14**(4): p. 207-217.
- 25 18. Suckling, J.R., et al., *Finite Conductance Governs the Resonance Transmission of Thin*
26 *Metal Slits at Microwave Frequencies*. Physical Review Letters, 2004. **92**(14): p. 147401.
- 27 19. Supplementary Material
- 28 20. R.J. Hicken, P.S. Keatley, and A.P. Hibbins, *Radio frequency detectable device*
29 *International Patent Number WO2014/195678 (2014)*
30